

Compatibility Matrix

Ultrastar® Data102

Firmware 4011-005 (SEP), 4.0.111 (OOBM)

Document D018-000234-000

Revision 20

April 2025



The Western Digital System Integration Lab tested the Ultrastar Data102 for the following hardware components and operating systems to demonstrate functional compatibility. Other combinations of hardware and software are expected to function with this product family but have not been evaluated.

Newly qualified device models are listed by category on the right. To use this document, click on the provided link to be taken to a detailed listing of the compatibility information for that specific device type. Or scroll down to view details for all tested devices.

HBAs & RAID Adapters

- [Adaptec® 1100-8e](#)
- [Areca® ARC-1886-8x, 1883x](#)
- [Broadcom® 9300-8e, -4i4e, -16e](#)
- [9302-16e](#)
- [9305-16e](#)
- [MegaRAID 9380-8e](#)
- [9400-16e, -8i8e, -8e](#)
- [9405w-16e](#)
- [MegaRAID 9480-8i8e](#)
- [9500-8e, -16e](#)
- [MegaRAID 9580-8i8e](#)
- [9600-16e](#)
- [9600w-16e](#)
- [Oracle 9300-8e](#)

Ultrastar Drives

- [DC HC510 CMR 8TB](#)
- [DC HC510 CMR 10TB](#)
- [DC HC530 CMR 14TB](#)
- [DC HC550 CMR 16TB](#)
- [DC HC550 CMR 18TB](#)
- [DC HC555 CMR 12TB](#)
- [DC HC555 CMR 14TB](#)
- [DC HC555 CMR 16TB](#)
- [DC HC555 CMR 18TB](#)
- [DC HC555 CMR 20TB](#)
- [DC HC560 CMR 20TB](#)
- [DC HC570 CMR 22TB](#)
- [DC HC580 CMR 22TB](#)
- [DC HC580 CMR 24TB](#)
- [DC HC650 SMR 20TB](#)
- [DC HC590 CMR 24TB](#)
- [DC HC590 CMR 26TB](#)
- [DC HC670 SMR 26TB](#)
- [DC HC680 SMR 26TB](#)
- [DC HC690 SMR 30TB](#)

Cables

- [Active \(Optical\) – 2m, 3m 4m, 5m, 6m, 10m](#)
- [Passive \(Copper\) – 2m, 3m](#)

1.1 HBA Compatibility

Adaptec 1100-8e

Table 1: Adaptec1100-8e Interoperability Notes

	Linux	Windows
Firmware	6.81	6.81
Driver	2.1.28-025	1010.96.0.1007
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Not Tested
	9.0 (x86_64) Kernel: 5.14.0-70	Not Tested
	9.2 (x86_64) Kernel: 5.14.0-284	Not Tested
	9.3 (x86_64) Kernel: 5.14.0-362	Not Tested
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 files system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Areca ARC-1886-8x, 1883x*Table 2: ArecaARC-1886-8x, 1883x Interoperability Notes*

	Linux	Windows
Firmware	1.58	1.58
Driver	1.50.0X.07	6.20.00.38
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Not Tested
	22.04 Kernel: 5.15	Not Tested
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux . If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 files system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom 9300-8e, -4i4e, -16e

Table 3: Broadcom9300-8e, -4i4e, -16e Interoperability Notes

	Linux	Windows
Firmware	16.00.17.00	16.00.17.00
Driver	39.100.00.00 CentOS/RHEL 8.0 and above: 41.00.00.00-1	2.51.27.01
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Supported
	10 Kernel: 4.19	Supported
	11 Kernel: 5.10	Supported
Oracle Linux (OL)	7.9 Kernel: UEK r6	Supported
FreeBSD®	13.2	Not Tested



Note: To increase the responsiveness of the topology during the event of a cable pull, IOM/ESM reset, or drive pull, use ScrutinyCLI (version 32 or later) to change the **Task Management Reset Type** on the HBA(s) from **Target Reset** to **I_T Nexus Reset**, and change the DMD settings on the HBA from 0 to 21 seconds. See https://support-en.westerndigital.com/app/answers/detail/a_id/32058 for more details.



Important: Active Optical SAS cable support is limited to Broadcom 9300-, 9302-, 9305-, 9400-, 9500-, and 9600-series HBAs.



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 files system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom 9302-16e

Table 4: Broadcom9302-16e Interoperability Notes

	Linux	Windows
Firmware	16.00.17.00	16.00.17.00
Driver	39.100.00.00	2.51.27.01
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Note: To increase the responsiveness of the topology during the event of a cable pull, IOM/ESM reset, or drive pull, use ScrutinyCLI (version 32 or later) to change the **Task Management Reset Type** on the HBA(s) from **Target Reset** to **I_T Nexus Reset**, and change the DMD settings on the HBA from 0 to 21 seconds. See https://support-en.westerndigital.com/app/answers/detail/a_id/32058 for more details.



Important: Active Optical SAS cable support is limited to Broadcom 9300-, 9302-, 9305-, 9400-, 9500-, and 9600-series HBAs.



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 file system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom 9305-16e

Table 5: Broadcom9305-16e Interoperability Notes

	Linux	Windows
Firmware	16.00.13.00	16.00.13.00
Driver	39.100.00.00	2.51.27.01
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Note: To increase the responsiveness of the topology during the event of a cable pull, IOM/ESM reset, or drive pull, use ScrutinyCLI (version 32 or later) to change the **Task Management Reset Type** on the HBA(s) from **Target Reset** to **I_T Nexus Reset**, and change the DMD settings on the HBA from 0 to 21 seconds. See https://support-en.westerndigital.com/app/answers/detail/a_id/32058 for more details.



Important: Active Optical SAS cable support is limited to Broadcom 9300-, 9302-, 9305-, 9400-, 9500-, and 9600-series HBAs.



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 file system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom MegaRAID 9380-8e

Table 6: Broadcom MegaRAID 9380-8e Interoperability Notes

	Linux	Windows
Firmware	24.21.0-0159	24.21.0-0159
Driver	07.723.02.00	06.714.18.00
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 files system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom 9400-16e, -8i8e, -8e

Table 7: Broadcom9400-16e, -8i8e, -8e Interoperability Notes

	Linux	Windows
Firmware	24.00.00.00	24.00.00.00
Driver	43.00.00.00-1	2.61.48.00
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Supported
	11 Kernel: 5.10	Supported
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Note: To increase the responsiveness of the topology during the event of a cable pull, IOM/ESM reset, or drive pull, use ScrutinyCLI (version 32 or later) to change the **Task Management Reset Type** on the HBA(s) from **Target Reset** to **I_T Nexus Reset**, and change the DMD settings on the HBA from 0 to 21 seconds. See https://support-en.westerndigital.com/app/answers/detail/a_id/32058 for more details.



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux . If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 files system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom 9405w-16e

Table 8: Broadcom9405w-16e Interoperability Notes

	Linux	Windows
Firmware	24.00.00.00	24.00.00.00
Driver	43.00.00.00-1	2.61.48.00
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Note: To increase the responsiveness of the topology during the event of a cable pull, IOM/ESM reset, or drive pull, use ScrutinyCLI (version 32 or later) to change the **Task Management Reset Type** on the HBA(s) from **Target Reset** to **I_T Nexus Reset**, and change the DMD settings on the HBA from 0 to 21 seconds. See https://support-en.westerndigital.com/app/answers/detail/a_id/32058 for more details.



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux . If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 files system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom MegaRAID 9480-8i8e

Table 9: Broadcom MegaRAID 9480-8i8e Interoperability Notes

	Linux	Windows
Firmware	51.23.0-4637	51.23.0-4637
Driver	07.724.02.00-1	07.724.02.00-1
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 file system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom 9500-8e, -16e

Table 10: Broadcom 9500-8e, -16e Interoperability Notes

	Linux	Windows	FreeBSD
Firmware	31.00.00.00	31.00.00.00	25.00.00.00
Driver	50.00.00.00-1	2.61.69.00	23.00.00.00
Operating System Support			
Microsoft® Windows	2019 R1 x64 Server		Supported
	2022 R1 x64 Server		Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477		Supported
	9.0 (x86_64) Kernel: 5.14.0-70		Supported
	9.2 (x86_64) Kernel: 5.14.0-284		Supported
	9.3 (x86_64) Kernel: 5.14.0-362		Supported
Ubuntu® Server	20.04 Kernel: 5.4		Supported
	22.04 Kernel: 5.15		Supported
Debian GNU/Linux	9.8 Kernel: 4.9		Not Tested
	10 Kernel: 4.19		Not Tested
	11 Kernel: 5.10		Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6		Supported
FreeBSD®	13.2		Supported ¹



Note: To increase the responsiveness of the topology during the event of a cable pull, IOM/ESM reset, or drive pull, use ScrutinyCLI (version 32 or later) to change the **Task Management Reset Type** on the HBA(s) from **Target Reset** to **I_T Nexus Reset**, and change the DMD settings on the HBA from 0 to 21 seconds. See https://support-en.westerndigital.com/app/answers/detail/a_id/32058 for more details.



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 files system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

1. WDDCS tool and sg_scan tool will not work in FreeBSD. Camcontrol tool, which has limited functionality, can be used.

Broadcom MegaRAID 9580-8i8e

Table 11: BroadcomMegaRAID 9580-8i8e Interoperability Notes

	Linux	Windows
Firmware	52.29.0-5442	52.29.0-5442
Driver	07.729.00.00-1	07.729.01.00
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 file system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom 9600-16e

Table 12: Broadcom 9600-16e Interoperability Notes

	Linux	Windows
Firmware	8.9.1.0-00000-00002	8.9.1.0-00000-00002
Driver	8.9.1.0.0	8.09.06.00
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux. If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 file system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Broadcom 9600w-16e

Table 13: Broadcom9600w-16e Interoperability Notes

	Linux	Windows
Firmware	8.9.1.0-00000-00002	8.9.1.0-00000-00002
Driver	8.9.1.0.0	8.09.06.00
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Supported
	2022 R1 x64 Server	Supported
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Not Tested
FreeBSD®	13.2	Not Tested



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux . If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 files system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

Oracle 9300-8e

Table 14: Oracle 9300-8e Interoperability Notes

	Linux	Windows
Firmware	16.00.08.00	N/A
Driver	39.100.00.00	N/A
Operating System Support		
Microsoft® Windows	2019 R1 x64 Server	Not Tested
	2022 R1 x64 Server	Not Tested
CentOS/RedHat® Enterprise Linux (RHEL)	8.8 (x86_64) Kernel: 4.18.0-477	Supported
	9.0 (x86_64) Kernel: 5.14.0-70	Supported
	9.2 (x86_64) Kernel: 5.14.0-284	Supported
	9.3 (x86_64) Kernel: 5.14.0-362	Supported
Ubuntu® Server	20.04 Kernel: 5.4	Supported
	22.04 Kernel: 5.15	Supported
Debian GNU/Linux	9.8 Kernel: 4.9	Not Tested
	10 Kernel: 4.19	Not Tested
	11 Kernel: 5.10	Not Tested
Oracle Linux (OL)	7.9 Kernel: UEK r6	Supported
FreeBSD®	13.2	Not Tested



Attention: For all HBAs using CentOS/RedHat® Enterprise Linux (RHEL), Ubuntu® Server, or Debian GNU/Linux . If the drives being used exceed 16TiB (equivalent to 16.37 TB) capacity, you must use the Ext4 or XFS file system. Using the Ext3 file system with a drive capacity higher than 16TiB (equivalent to 16.37 TB) will result in an **"too big to be expressed"** error message.

1.2 Cable Compatibility

Active (Optical) Cables

Active cables can be used for both direct (host-to-enclosure) and daisy-chain (enclosure-to-enclosure) connections.



Important: Active Optical SAS cable support is limited to Broadcom 9300-, 9302-, 9305-, 9400-, 9500-, and 9600-series HBAs.



Note: MegaRAID adapters do not support the use of active SAS cables. If your configuration requires the use of MegaRAID adapters, passive cables must be used.

Table 15: Approved Active Optical HD Mini-SAS to HD Mini-SAS Cables

Length	Manufacturer	Vendor Part Number
2m	JPC Connectivity (Jess-Link)	P5388FC3002M-1 ²
3m	Amphenol ICC (FCI)	FOHHB23P00003 ³
	JPC Connectivity (Jess-Link)	P5388FC3003M-1
	Molex	106415-2103
4m	Amphenol ICC (FCI)	FOHHB23P00004
	JPC Connectivity (Jess-Link)	P5388FC3004M-1
	JPC Connectivity (Jess-Link)	P5388FC3004M-3
5m	Amphenol ICC (FCI)	FOHHB23P00005
	Molex	106415-2105
6m	Amphenol ICC (FCI)	FOHHB23P00006
	JPC Connectivity (Jess-Link)	P5388FC3006M-1
10m	Molex	106415-2110

2. Listed JPC P5388FC300xxx cables are compatible, beginning with firmware version 4008-020 and later.

3. Listed FOHHB23P00xxx cables are compatible, beginning with firmware version 2052-020 and later.

Passive (Copper) Cables

Passive cables should only be used for direct (host-to-enclosure) connections.

Table 16: Approved Passive HD Mini-SAS to HD Mini-SAS Cables

Length	Manufacturer	Vendor Part Number
1m	Amphenol ICC (FCI)	10112041-2010LF
2m	Amphenol ICC (FCI)	601760006
		10117949-2020LF
		10112041-2020LF
	CS Electronics	12G-HD-4444/2M
	Data Storage Cables (DSC)	C5555-2M
	Molex	1110751002
3m	Amphenol ICC (FCI)	C5555-2M
		601760008
		10117949-4030LF
	CS Electronics	10112041-2030LF
	Molex	12G-HD-4444/3M
		1110751003

1.3 HDD Compatibility

Ultrastar DC HC310 CMR, 6TB HDD with 3.5" Drive Carrier

Table 17: DC HC310 Part / Model Numbers

Sector Size	SATA		SAS		
	SE	TCG	SE	TCG	TCG-FIPS
512e	1EX1189 / HUS726T6TAL-E604	1EX1188 / HUS726T6TAL-E601	1EX1185 / HUS726T6TAL-5204	1EX1184 / HUS726T6TAL-5201	1EX1853 / HUS726T6TAL-5205
4Kn	1EX1187 / HUS726T6TAL-N604	1EX1186 / HUS726T6TAL-N601	1EX1183 / HUS726T6TAL-4204	1EX1182 / HUS726T6TAL-4201	1EX1852 / HUS726T6TAL-4205

Ultrastar DC HC320 CMR, 8TB HDD with 3.5" Drive Carrier

Table 18: DC HC320 Part / Model Numbers

Sector Size	SATA			SAS		
	SE	SED	TCG	SE	TCG	TCG-FIPS
512e	1EX1227 / HUS728T8TAL-E604	1EX1226 / HUS728T8TAL-E601		1EX1223 / HUS728T8TAL-5204	1EX1222 / HUS728T8TAL-5201	1EX1343 / HUS728T8TAL-5205
4Kn	1EX1225 / HUS728T8TAL-N604		1EX1224 / HUS728T8TAL-N601	1EX1221 / HUS728T8TAL-4204	1EX1220 / HUS728T8TAL-4201	1EX1342 / HUS728T8TAL-4205

Ultrastar DC HC330 CMR, 10TB HDD with 3.5" Drive Carrier

Table 19: DC HC330 Part / Model Numbers

Sector Size	SATA		SAS		
	SE	SED	SE	TCG	TCG-FIPS
512e	1EX2440 / WUS721010AL-E604	1EX2441 / WUS721010AL-E601	1EX2435 / WUS721010AL-5204	1EX2436 / WUS721010AL-5201	1EX2437 / WUS721010AL-5205
4Kn	1EX2438 / WUS721010AL-N604	1EX2439 / WUS721010AL-N601	1EX2432 / WUS721010AL-4204	1EX2433 / WUS721010AL-4201	1EX2434 / WUS721010AL-4205

Ultrastar DC HC510 CMR, 8TB HDD with 3.5" Drive Carrier

Table 20: DC HC510 Part / Model Numbers

Sector Size	SAS
	ISE
512e	1EX0392 / HUH721008AL-5200

Ultrastar DC HC510 CMR, 10TB HDD with 3.5" Drive Carrier

Table 21: DC HC510 Part / Model Numbers

Sector Size	SATA			SAS			
	SE	ISE	SED	SE	ISE	TCG	TCG-FIPS
512e	1EX0499 / HUH721010AL-E604	1EX0497 / HUH721010AL-E600	1EX0498 / HUH721010AL-E601	1EX0487 / HUH721010AL-5204	1EX0485 / HUH721010AL-5200	1EX0486 / HUH721010AL-5201	1EX1341 / HUH721010AL-5205
4Kn	1EX0496 / HUH721010AL-N604	1EX0494 / HUH721010AL-N600	1EX0495 / HUH721010AL-N601	1EX0484 / HUH721010AL-4204	1EX0482 / HUH721010AL-4200	1EX0483 / HUH721010AL-4201	1EX1340 / HUH721010AL-4205

Ultrastar DC HC520 CMR, 12TB HDD with 3.5" Drive Carrier

Table 22: DC HC520 Part / Model Numbers

Sector Size	SATA			SAS			
	SE	ISE	SED	SE	ISE	TCG	TCG-FIPS
512e	1EX1015 / HUH721212AL-E604	1EX1013 / HUH721212AL-E600	1EX1014 / HUH721212AL-E601	1EX1009 / HUH721212AL-5204	1EX1007 / HUH721212AL-5200	1EX1008 / HUH721212AL-5201	1EX1338 / HUH721212AL-5205
4Kn	1EX1012 / HUH721212AL-N604	1EX1010 / HUH721212AL-N600	1EX1011 / HUH721212AL-N601	1EX1006 / HUH721212AL-4204	1EX1004 / HUH721212AL-4200	1EX1005 / HUH721212AL-4201	1EX1339 / HUH721212AL-4205

Ultrastar DC HC530 CMR, 14TB HDD with 3.5" Drive Carrier

Attention: Lower performance observed for multiple (2, 4, and 8) write streams when using I/O Queue Depths of less than 4 on Ultrastar DC HC530 14TB SAS drives.

Table 23: DC HC530 Part / Model Numbers

Sector Size	SATA		SAS			
	SE	SED	SE	ISE	TCG	TCG-FIPS
512e	1EX1793* / WUH721414AL-E604	1EX1794* / WUH721414AL-E6L1	1EX1791* / WUH721414AL-5204 1EX3045 / WUH721814AL-5204	1EX1583 / WUH721414AL-5200	1EX1792* / WUH721414AL-5201	1EX1855 / WUH721414AL-5205
	1EX3046 / WUH721814AL-E6L4					
4Kn	1EX1790* / WUH721414AL-N604		1EX1788* / WUH721414AL-4204		1EX1789* / WUH721414AL-4201	1EX1854 / WUH721414AL-4205

* This part number is no longer available.

Ultrastar DC HC550 CMR, 16TB HDD with 3.5" Drive Carrier

Table 24: DC HC550 Part / Model Numbers

Sector Size	SATA		SAS		
	SE	SED	SE	TCG	TCG-FIPS
512e	1EX2476 / WUH721816AL-E604	1EX2477 / WUH721816AL-E601	1EX2473 / WUH721816AL-5204	1EX2474 / WUH721816AL-5201	1EX2475 / WUH721816AL-5205

Ultrastar DC HC550 CMR, 18TB HDD with 3.5" Drive Carrier

Table 25: DC HC550 Part / Model Numbers

Sector Size	SATA		SAS		
	SE	SED	SE	TCG	TCG-FIPS
512e	1EX2481 / WUH721818AL-E604	1EX2482 / WUH721818AL-E601	1EX2478 / WUH721818AL-5204	1EX2479 / WUH721818AL-5201	1EX2480 / WUH721818AL-5205

Ultrastar DC HC555 CMR, 12TB HDD with 3.5" Drive Carrier

Table 26: DC HC555 Part / Model Numbers

Sector Size	SATA		SAS	
	SE		SE	TCG
512e	1EX3306 / WUH722012CL-E604		1EX3305 / WUH722012CL-5204	1EX3307 / WUH722012CL-5201

Ultrastar DC HC555 CMR, 14TB HDD with 3.5" Drive Carrier

Table 27: DC HC555 Part / Model Numbers

Sector Size	SATA	SAS	
	SE	SE	TCG
512e	1EX3309 / WUH722014CL- E604	1EX3308 / WUH722014CL-5204	1EX3310 / WUH722014CL-5201

Ultrastar DC HC555 CMR, 16TB HDD with 3.5" Drive Carrier

Table 28: DC HC555 Part / Model Numbers

Sector Size	SATA	SAS	
	SE	SE	TCG
512e	1EX3312 / WUH722016CL- E604	1EX3311 / WUH722016CL-5204	1EX3313 / WUH722016CL-5201

Ultrastar DC HC555 CMR, 18TB HDD with 3.5" Drive Carrier

Table 29: DC HC555 Part / Model Numbers

Sector Size	SATA	SAS	
	SE	SE	TCG
512e	1EX3315 / WUH722018CL-E604	1EX3314 / WUH722018CL-5204	1EX3316 / WUH722018CL-5201

Ultrastar DC HC555 CMR, 20TB HDD with 3.5" Drive Carrier

Table 30: DC HC555 Part / Model Numbers

Sector Size	SATA	SAS	
	SE	SE	TCG
512e	1EX3318 / WUH722020CL-E604	1EX3317 / WUH722020CL-5204	1EX3319 / WUH722020CL-5201

Ultrastar DC HC560 CMR, 20TB HDD with 3.5" Drive Carrier

Table 31: DC HC560 Part / Model Numbers

Sector Size	SATA		SAS	
	SE	SED	SE	TCG
512e	1EX2909 / WUH722020BL- E604	1EX2910 / WUH722020BL- E601	1EX2906 / WUH722020BL- 5204	1EX2907 / WUH722020BL- 5201

Ultrastar DC HC570 CMR, 22TB HDD with 3.5" Drive Carrier

Table 32: DC HC570 Part / Model Numbers

Sector Size	SATA		SAS	
	SE	SED	SE	TCG
512e	1EX2966 / WUH722222AL-E604	1EX2967 / WUH722222AL-E601	1EX2963 / WUH722222AL-5204	1EX2964 / WUH722222AL-5201

Ultrastar DC HC580 CMR, 22TB HDD with 3.5" Drive Carrier

Table 33: DC HC580 Part / Model Numbers

Sector Size	SATA	SAS
	SE	SE
512e	1EX3169 / WUH722422AL-5201	1EX3168 / WUH722424AL-5201

Sector Size	SATA		SAS	
	SE	SED	SE	TCG
512e	1EX2966 / WUH722222AL-E604	1EX2967 / WUH722222AL-E601	1EX2963 / WUH722222AL-5204	1EX2964 / WUH722222AL-5201

Ultrastar DC HC580 CMR, 24TB HDD with 3.5" Drive Carrier

Table 35: DC HC580 Part / Model Numbers

Sector Size	SATA	SAS	
	SE	SE	TCG
512e	1EX3171 / WUH722424AL-E6L4	1EX3170 / WUH722424AL5204	
4Kn			1EX3230 / WUH722424AL5201

Ultrastar DC HC650 SMR, 20TB HDD with 3.5" Drive Carrier

Table 36: DC HC650 Part / Model Numbers

Sector Size	SATA		SAS	
	SE	SED	SE	TCG
4Kn	1EX2719 / WSH722020AL-N604	1EX2720 / WSH722020AL-N601	1EX2716 / WSH722020AL-4204	1EX2717 / WSH722020AL-4201

Ultrastar DC HC650 drives are only compatible with the OSs and HBAs listed in the following table:

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 18.04	4.15.0-76-generic	9300-8e	22.00.00.00	43.00.00.00

OS	Kernel	HBA	HBA FW	HBA Driver
		9300-16e	30.00.00.00	49.00.00.00
		9300-4i4e		
		9400-8e		
		9405-16e		
		9500-8e		
		9500-16e		
Ubuntu 20.04	5.4.0-47-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e		
		9500-8e		
Ubuntu 22.04	5.15	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e		
		9500-8e		
CentOS/RedHat Enterprise Linux (RHEL)	5.14.0.70.13.1	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e		
		9500-8e		
		9500-16e	30.00.00.00	49.00.00.00

Ultrastar DC HC590 CMR, 24TB HDD with 3.5" Drive Carrier

Table 38: DC HC590 Part / Model Numbers

Sector Size	SATA	SAS	
	SE	SE	TCG
512e	1EX3268 / WUH722624ALN604	1EX3267 / WUH722624AL4204	1EX3327 / WUH722624AL4201

Ultrastar DC HC590 drives are only compatible with the OSs and HBAs listed in the following table:

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 18.04	4.15.0-76-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	28.00.00.00	47.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.8.1.0.0	8.8.1.0
		9600w-16e		
Ubuntu 20.04	5.4.0-47-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		
Ubuntu 22.04	5.15	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		
CentOS/RedHat Enterprise Linux (RHEL)	5.14.0.70.13.1	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0

OS	Kernel	HBA	HBA FW	HBA Driver
		9600w-16e		

Ultrastar DC HC590 CMR, 26TB HDD with 3.5" Drive Carrier

Table 40: DC HC590 Part / Model Numbers

Sector Size	SATA	SAS	
	SE	SE	TCG
512e	1EX3270 / WUH722626ALN604	1EX3269 / WUH722626AL4204	1EX3328 / WUH722626AL4201

Ultrastar DC HC590 drives are only compatible with the OSs and HBAs listed in the following table:

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 18.04	4.15.0-76-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	28.00.00.00	47.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.8.1.0.0	8.8.1.0
		9600w-16e		
Ubuntu 20.04	5.4.0-47-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		
Ubuntu 22.04	5.15	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e		

OS	Kernel	HBA	HBA FW	HBA Driver
CentOS/RedHat Enterprise Linux (RHEL)	5.14.0.70.13.1	9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		
		9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		

Ultrastar DC HC670 SMR, 26TB HDD with 3.5" Drive Carrier

Table 42: DC HC670 Part / Model Numbers

Sector Size	SATA		SAS	
	SE	SED	SE	TCG
4Kn	1EX3013 / WSH722626ALN604	1EX3014 / WSH722626ALN601	1EX3010 / WSH722626AL4204	1EX3011 / WSH722626AL4201

Ultrastar DC HC670 drives are only compatible with the OSs and HBAs listed in the following table:

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 18.04	4.15.0-76-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	28.00.00.00	47.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.8.1.0.0	8.8.1.0
		9600w-16e		
Ubuntu 20.04	5.4.0-47-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	31.00.00.00	50.00.00.00
		9500-8e		

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 22.04	5.15	9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
		9600w-16e		
		9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
		9600w-16e		
CentOS/RedHat Enterprise Linux (RHEL)	5.14.0.70.13.1	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
		9600w-16e		

Ultrastar DC HC680 SMR, 26TB HDD with 3.5" Drive Carrier

Table 44: DC HC680 Part / Model Numbers

Sector Size	SATA
	SE
4Kn	1EX3172 / WSH722860ALN6L4

Ultrastar DC HC680 drives are only compatible with the OSs and HBAs listed in the following table:

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 18.04	4.15.0-76-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e		47.00.00.00

OS	Kernel	HBA	HBA FW	HBA Driver
		9500-8e	28.00.00.00	
		9500-16e		
		9600-16e	8.8.1.0.0	8.8.1.0
		9600w-16e		
Ubuntu 20.04	5.4.0-47-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
Ubuntu 22.04	5.15	9600w-16e		
		9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
CentOS/RedHat Enterprise Linux (RHEL)	5.14.0.70.13.1	9600w-16e		
		9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
		9600w-16e		

Ultrastar DC HC680 SMR, **27TB** HDD with 3.5" Drive Carrier

Table 46: DC HC680 Part / Model Numbers

Sector Size	SATA
	SE
4Kn	1EX3173 / WSH722870ALN6L4

Ultrastar DC HC680 drives are only compatible with the OSs and HBAs listed in the following table:

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 18.04	4.15.0-76-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	28.00.00.00	47.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.8.1.0.0	8.8.1.0
		9600w-16e		
Ubuntu 20.04	5.4.0-47-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		
Ubuntu 22.04	5.15	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		
CentOS/RedHat Enterprise Linux (RHEL)	5.14.0.70.13.1	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		

OS	Kernel	HBA	HBA FW	HBA Driver
		9400-8e	31.00.00.00	50.00.00.00
		9400-16e		
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
		9600w-16e		

Ultrastar DC HC680 SMR, 28TB HDD with 3.5" Drive Carrier

Table 48: DC HC680 Part / Model Numbers

Sector Size	SATA
	SE
4Kn	1EX3174 / WSH722880ALN6L4

Ultrastar DC HC680 drives are only compatible with the OSs and HBAs listed in the following table:

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 18.04	4.15.0-76-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e	28.00.00.00	47.00.00.00
		9405-16e		
		9500-8e		
		9500-16e	8.8.1.0.0	8.8.1.0
		9600-16e		
		9600w-16e		
Ubuntu 20.04	5.4.0-47-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e	31.00.00.00	50.00.00.00
		9405-16e		
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
		9600w-16e		
Ubuntu 22.04	5.15	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		

OS	Kernel	HBA	HBA FW	HBA Driver
		9300-4i4e		
		9400-8e		
		9400-16e		
		9500-8e	31.00.00.00	50.00.00.00
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		
CentOS/RedHat Enterprise Linux (RHEL)	5.14.0.70.13.1	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
		9600w-16e		

Ultrastar DC HC690 SMR, 30TB HDD with 3.5" Drive Carrier

Table 50: DC HC690 Part / Model Numbers

Sector Size	SATA	SAS	
	SE	SE	TCG
4Kn	1EX3272 / WSH723200ALN604	1EX3271 / WSH723200AL4204	1EX3329 / WSH723200AL4201

Ultrastar DC HC690 drives are only compatible with the OSs and HBAs listed in the following table:

OS	Kernel	HBA	HBA FW	HBA Driver
Ubuntu 18.04	4.15.0-76-generic	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e	28.00.00.00	47.00.00.00
		9500-8e		
		9500-16e	8.8.1.0.0	8.8.1.0
		9600-16e		
		9600w-16e		
Ubuntu 20.04	5.4.0-47-generic	9300-8e	22.00.00.00	43.00.00.00

OS	Kernel	HBA	HBA FW	HBA Driver
		9300-16e		
		9300-4i4e		
		9400-8e		
		9405-16e		
		9500-8e	31.00.00.00	50.00.00.00
		9500-16e		
		9600-16e	8.9.1.0	8.9.1.0.0
		9600w-16e		
Ubuntu 22.04	5.15	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
CentOS/RedHat Enterprise Linux (RHEL)	5.14.0.70.13.1	9300-8e	22.00.00.00	43.00.00.00
		9300-16e		
		9300-4i4e		
		9400-8e		
		9400-16e	31.00.00.00	50.00.00.00
		9500-8e		
		9500-16e	8.9.1.0	8.9.1.0.0
		9600-16e		
		9600w-16e		

1.4 Compatible SSDs



Attention: All drives have been tested with version 4011-005 enclosure firmware.

Device	Volume	Encryption	Drive Firmware	Manufacturer Part Number
Kioxia SAS PM7-M/V/R Series SSD	Up to 3.84TB	SE	0101	KPM7XRUG3T84

Device	Volume	Encryption	Drive Firmware	Manufacturer Part Number
Samsung SAS PM1653A SSD	Up to 3.84TB	SE	GXG3	MZILG3T8HCLS-00A07



Note: Ultrastar Data102 supports third-party device features that are within SAS specification as mandatory. Any third-party drive features that are vendor specific are not guaranteed to function.

1.5 Non-TAA SKUs for Fully Populated Configurations

Table 53: Fully Populated Configurations

Capacity	Drive Type	Sector Size	SATA			SAS			
			SE	SED	ISE	SE	ISE	TCG	TCG-FIPS
3060TB	HC690	4Kn	1ES2728			1ES2725		1ES2861	
2652TB	HC590	512e	1ES2733			1ES2731		1ES2867	
2448TB	HC590	512e	1ES2739			1ES2737		1ES2864	
	HC580		1ES2484						
			1ES2498						
2244TB	HC580	512e	1ES2480						
			1ES2494						
	HC570		1ES2191	1ES2192		1ES2061		1ES2186	
2040TB	HC560	512e	1ES2151	1ES2152		1ES2155		1ES2153	
	HC555		1ES2805			1ES2803		1ES2809	
1836TB	HC550	512e	1ES1851	1ES1852		1ES1885		1ES1846	
	HC555		1ES2796			1ES2794		1ES2800	
1632TB	HC550	512e	1ES1861	1ES1862		1ES1855		1ES1856	
	HC555		1ES2787			1ES2785		1ES2791	
1428TB	HC555	512e	1ES2777			1ES2775		1ES2782	
	HC550		1ES2337			1ES2336			
			1ES2340			1ES2341			
	HC530	512e	1ES1452*	1ES1453*		1ES1450*		1ES1451*	1ES1999*
		4Kn	1ES1449*			1ES1447*		1ES1448*	
1224TB	HC555	512e	1ES2768			1ES2766		1ES2772	
	HC520		1ES0317	1ES0316	1ES0315	1ES0311	1ES0309	1ES0310	
			4Kn	1ES0314	1ES0313	1ES0312	1ES0308	1ES0306	1ES0307
1020TB	HC330	512e	1ES1815	1ES1814		1ES1807		1ES1802	
		4Kn	1ES1816	1ES1817		1ES1804		1ES1805	
816TB	HC320	512e	1ES1225	1ES1224		1ES1221		1ES1220	
		4Kn	1ES1223	1ES1222		1ES1219		1ES1218	
612TB	HC310	512e	1ES1146	1ES1145		1ES1142		1ES1141	
		4Kn	1ES1144	1ES1143		1ES1135		1ES1134	

* This part number is no longer available.

1.6 Non-TAA SKUs for Partially Populated Configurations

Table 54: Partially Populated Configurations

Capacity	Drive Type	Sector Size	SATA			SAS			
			SE	SED	ISE	SE	ISE	TCG	TCG-FIPS
1800TB	HC690	4Kn	1ES2729			1ES2726		1ES2862	
1560TB	HC590	512e	1ES2734			1ES2732		1ES2868	
1440TB	HC590	512e	1ES2740			1ES2738		1ES2865	
	HC580		1ES2485						
			1ES2499						
1320TB	HC580	512e	1ES2481						
			1ES2495						
	HC570		1ES2193	1ES2194		1ES2188		1ES2189	
1200TB	HC560	512e	1ES2156	1ES2157		1ES2158		1ES2159	
	HC555		1ES2806			1ES2804		1ES2810	
1080TB	HC555	512e	1ES2797			1ES2795		1ES2801	
	HC550		1ES1853	1ES1854		1ES1848		1ES1849	
960TB	HC555	512e	1ES2788			1ES2786		1ES2792	
	HC550		1ES1863	1ES1864		1ES1858		1ES1859	
840TB	HC555	512e	1ES2778			1ES2776		1ES2783	
	HC550		1ES2343			1ES2342			
			1ES2339			1ES2338			
			1ES1459*	1ES1460*		1ES1457*	1ES1494	1ES1458*	
	HC530	4Kn	1ES1456*			1ES1454*		1ES1455*	
720TB	HC555	512e	1ES2769			1ES2767		1ES2773	
	HC520		1ES0341	1ES0340	1ES0339	1ES0335	1ES0333	1ES0334	
			4Kn	1ES0338	1ES0337	1ES0336	1ES0332	1ES0330	1ES0331
600TB	HC330	512e	1ES1818	1ES1819		1ES1808		1ES1809	
		4Kn	1ES1820	1ES1821		1ES1811		1ES1812	
480TB	HC320	512e	1ES1233	1ES1232		1ES1229		1ES1228	
		4Kn	1ES1231	1ES1230		1ES1227		1ES1226	
360TB	HC310	512e	1ES1154	1ES1153		1ES1150		1ES1149	
		4Kn	1ES1152	1ES1151		1ES1148		1ES1147	

* This part number is no longer available.

1.7 TAA SKUs for Fully Populated Configurations

Table 55: Fully Populated Configurations

Capacity	Drive Type	Sector Size	SATA			SAS			
			SE	SED	ISE	SE	ISE	TCG	TCG-FIPS
3060TB	HC690	4Kn	1ES2730			1ES2727		1ES2863	
2652TB	HC590	512e	1ES2736			1ES2735		1ES2869	
2448TB	HC590	512e						1ES2866	
2244TB	HC590	512e	1ES2742			1ES2741			
			1ES2509						
	HC580		1ES2516						
			1ES2507						
	HC580		1ES2514						
2040TB	HC570		1ES2211	1ES2197		1ES2212		1ES2195	
	HC560	512e	1ES2213	1ES2180		1ES2214		1ES2178	
	HC555		1ES2808			1ES2807		1ES2811	
1836TB	HC555	512e	1ES2799			1ES2798		1ES2802	
	HC550		1ES2215	1ES2089		1ES2216		1ES2087	1ES2088
1632TB	HC555	512e	1ES2790			1ES2789		1ES2793	
	HC550		1ES2217	1ES2086		1ES2218		1ES2084	1ES2085
1428TB	HC555	512e	1ES2781			1ES2779		1ES2784	
	HC550		1ES2335			1ES2334			
	HC530		1ES2219*	1ES2083*		1ES2220*		1ES2081*	1ES2082*
1224TB	HC555	512e	1ES2771			1ES2770		1ES2774	
	HC520		1ES2221	1ES2126		1ES2222		1ES2122	1ES2123

* This part number is no longer available.

1.8 Non-TAA SKUs for Scale-Up Modules

Table 56: 14-Pack nTAA Scale-Up Modules

Capacity	Drive Type	Sector Size	SATA			SAS			
			SE	SED	ISE	SE	ISE	TCG	TCG-FIPS
364TB	HC670	4Kn	1EX3003	1EX3004		1EX3000		1EX3001	
336TB	HC580	512e	1EX3157						
308TB	HC580	512e	1EX3155						
	HC570		1EX2956	1EX2957		1EX2953		1EX2954	
280TB	HC560	512e	1EX2899	1EX2900		1EX2891		1EX2892	
	HC555		1EX3288			1EX3287		1EX3289	
252TB	HC555	512e	1EX3285			1EX3284		1EX3286	
	HC550		1EX2471	1EX2472		1EX2468		1EX2469	1EX2470
224TB	HC555	512e	1EX3282			1EX3281			
	HC550		1EX2466	1EX2467		1EX2463		1EX2464	1EX2465
196TB	HC555	512e	1EX3279			1EX3278		1EX3280	
	HC550		1EX3042			1EX3041			
	HC530	4Kn	1EX1840*	1EX1841*		1EX1838*		1EX1839*	
168TB	HC555	512e	1EX1837*			1EX1835*		1EX1836*	
			1EX3276			1EX3275		1EX3277	
	HC520	4Kn	1EX0535		1EX0533	1EX0529	1EX0527	1EX0528	
140TB	HC330	512e	1EX0532		1EX0530	1EX0526	1EX0524	1EX0525	
		4Kn	1EX2450	1EX2451		1EX2445		1EX2446	
112TB	HC320	512e	1EX2448	1EX2449		1EX2442		1EX2443	
		4Kn	1EX1235	1EX1234		1EX1231		1EX1230	
84TB	HC310	512e	1EX1233	1EX1232		1EX1229		1EX1228	
		4Kn	1EX1197	1EX1196		1EX1193		1EX1192	
			1EX1195	1EX1194		1EX1191		1EX1190	

* This part number is no longer available.

Table 57: 12-Pack nTAA Scale-Up Modules

Capacity	Drive Type	Sector Size	SATA			SAS			
			SE	SED	ISE	SE	ISE	TCG	TCG-FIPS
420TB	HC690	4Kn	1EX3260			1EX3259		1EX3323	
364TB	HC590	512e	1EX3258			1EX3257		1EX3322	
360TB	HC690	4Kn	1EX3266			1EX3265		1EX3326	
336TB	HC590	512e	1EX3256			1EX3255		1EX3321	
312TB	HC670	4Kn	1EX3008	1EX3009		1EX3005		1EX3006	
	HC590	512e	1EX3264			1EX3263		1EX3325	
288TB	HC590	512e	1EX3262			1EX3261		1EX3324	
	HC580		1EX3164						
264TB	HC580	512e	1EX3162						
	HC570		1EX2961	1EX2962		1EX2958		1EX2959	
240TB	HC560	512e	1EX2904	1EX2905		1EX2901		1EX2902	
	HC555		1EX3303			1EX3302		1EX3304	
216TB	HC555	512e	1EX3300			1EX3299		1EX3301	
	HC550		1EX2491	1EX2492		1EX2488		1EX2489	1EX2490
		4Kn				1EX2785			
192TB	HC555	512e	1EX3297			1EX3296		1EX3298	
	HC550		1EX2486	1EX2487		1EX2483		1EX2484	1EX2485
168TB	HC555	512e	1EX3294			1EX3293		1EX3295	
	HC550		1EX3044			1EX3043			
	HC530	4Kn	1EX1847*	1EX1848*		1EX1845*		1EX1846*	
	1EX1844*				1EX1842*		1EX1843*		
144TB	HC555	512e	1EX3291			1EX3290		1EX3292	
	HC520		1EX0553		1EX0551	1EX0547	1EX0545	1EX0546	
		4Kn	1EX0550		1EX0548	1EX0544	1EX0542	1EX0543	
120TB	HC330	512e	1EX2460	1EX2461		1EX2455		1EX2456	
		4Kn	1EX2458	1EX2459		1EX2452		1EX2453	
96TB	HC320	512e	1EX1243	1EX1242		1EX1239		1EX1238	
		4Kn	1EX1241	1EX1240		1EX1237		1EX1236	
72TB	HC310	512e	1EX1213	1EX1212		1EX1209		1EX1208	
		4Kn	1EX1211	1EX1210		1EX1207		1EX1206	
48TB	HC310	512e				1EX2250		1EX2251	1EX2252

Capacity	Drive Type	Sector Size	SATA			SAS			
			SE	SED	ISE	SE	ISE	TCG	TCG-FIPS
		4Kn				1EX2247		1EX2248	1EX2249

** This part number is no longer available.*

1.9 Notices

Western Digital Technologies, Inc. or its affiliates' (collectively "Western Digital") general policy does not recommend the use of its products in life support applications wherein a failure or malfunction of the product may directly threaten life or injury. Per Western Digital Terms and Conditions of Sale, the user of Western Digital products in life support applications assumes all risk of such use and indemnifies Western Digital against all damages.

This document is for information use only and is subject to change without prior notice. Western Digital assumes no responsibility for any errors that may appear in this document, nor for incidental or consequential damages resulting from the furnishing, performance or use of this material.

Absent a written agreement signed by Western Digital or its authorized representative to the contrary, Western Digital explicitly disclaims any express and implied warranties and indemnities of any kind that may, or could, be associated with this document and related material, and any user of this document or related material agrees to such disclaimer as a precondition to receipt and usage hereof.

Each user of this document or any product referred to herein expressly waives all guaranties and warranties of any kind associated with this document any related materials or such product, whether expressed or implied, including without limitation, any implied warranty of merchantability or fitness for a particular purpose or non-infringement. Each user of this document or any product referred to herein also expressly agrees Western Digital shall not be liable for any incidental, punitive, indirect, special, or consequential damages, including without limitation physical injury or death, property damage, lost data, loss of profits or costs of procurement of substitute goods, technology, or services, arising out of or related to this document, any related materials or any product referred to herein, regardless of whether such damages are based on tort, warranty, contract, or any other legal theory, even if advised of the possibility of such damages.

This document and its contents, including diagrams, schematics, methodology, work product, and intellectual property rights described in, associated with, or implied by this document, are the sole and exclusive property of Western Digital. No intellectual property license, express or implied, is granted by Western Digital associated with the document recipient's receipt, access and/or use of this document or the products referred to herein; Western Digital retains all rights hereto.

Western Digital, the Western Digital design, the Western Digital logo, and Ultrastar are registered trademarks or trademarks of Western Digital Corporation or its affiliates in the US and/or other countries. Windows is a trademark of the Microsoft group of companies. Linux® is the registered trademark of Linus Torvalds in the U.S. and other countries. CentOS and Red Hat Enterprise Linux are trademarks or registered trademarks of Red Hat, Inc. or its subsidiaries in the United States and other countries. Ubuntu is a registered trademark of Canonical Ltd. Broadcom is among the trademarks of Broadcom. All other marks are the property of their respective owners.

Product specifications subject to change without notice. Pictures shown may vary from actual products. Not all products are available in all regions of the world.

Western Digital
5601 Great Oaks Parkway
San Jose, CA 95119

© 2025 Western Digital Corporation or its affiliates. All Rights Reserved.

1.10 Points of Contact

For further assistance with a Western Digital product, contact Western Digital Datacenter Platforms technical support. Please be prepared to provide the following information, as applicable: part number (P/N), serial number (S/N), product name and/or model number, software version, and a brief description of the issue.

Website:

<https://portal.wdc.com/s/>

Email:

enterprisesupport@wdc.com

UK Import Representation Contact

PO Box 471
Leatherhead KT22 2LU
UK

Telephone: +44 1372 366000

EU Import Representation Contact

BP 80006
92135 Issy les Moulineaux, France